

## P2RFD-1672-SS

**Description**: 7-16 DIN adapters are highly desired in test applications such as base station PIM testing. These low loss, low VSWR "Rugged" adapters are designed to be used with portable antenna and cable analyzers. Anritsu's Site Master<sup>TM</sup>, Summitek's SI<sup>TM</sup> series and Boonton's PIM testers are examples where high grade DIN adapters are used. Some features to highlight are the Stainless Steel coupling nuts, White Bronze plated bodies for tarnish free service and superior electrical performance along with low passive intermodulation products. (PIM) White Bronze plating offers a non-magnetic solution while retaining high conductivity in the conductor paths. Engineered for long life in field applications, they are also suitable for lab environments. All 7-16 DIN adapters are machined to exacting specifications and stand up to the competition surpassing expectation when compared to typical Silver plated products. Test charts included.

Electrical:	Frequency range	DC to 8.0 GHz
	VSWR	<1.2:1 to 8.0 GHz, < 1.3:1 to 13 GHz
	Insertion Loss	
	3 <sup>rd</sup> Order IMP	>-170dBc in PCS band w/2 +43 dB tones
Mechanical:	Mating	M29 X 1.5mm; 5/8-24 UNEF Thread
	Interface	
	Mating cycles	
Materials and	d finish:	

Bod	y, Ground rings and Co	oupling Nuts.	. Brass,	BeCu,	SST, V	White	Bronze
Insı	ilator						PTFE
Pin	Contact	Brass, B	eCu; W.	B. over	Silver	over	Copper

**VSWR Chart:** 



PNA Series N ile View Chan				race Sc.	ale Marke	er Systen	n Windo	w Help			_ 2
Marker: 1 of 3		Mark	ker 1 8.00	000000000	GHz 🗧	Marke	r 1	Marker 2	Mark	er 3	Off
₩indow 1											_101
311 1 100UV	2.00	J \$11 P	2RFD-1672	-ss		> 1:		00000			1.1661
0.100U/ 1.00U SWR	1.90 -					1:	.8.	00000	GHz	-0.08	626 dE
321 ).500dB/ ).00dB LogM	1.80							-			
	1.70		-				0	· · · · ·		-	-
	1.60 -		-			-					
	1.50			~~~~~					······		
	1.40							-			
	1.30 -					2					
	1.20					9	8				
	1.10 -										
	1.00	Ch1: Star	t 300.000	kHz — —		B.				Stop 8.	.00000 GH
Cont. CH 1:	S11			C 2-Po	rt	D	elav Loss				LCL